

## Technical Data

### BA.A-C400

BA.A-C400  
320KW / 400KVA  
284KW / 356KVA

### Diesel Generating Set

MODEL  
Standby Power (50Hz)  
Prime Power (50Hz)

#### General Features:

- Engine (Cummins NTA 855 G4)
- Radiator 50C max, fans are driven by belt, with safety guard
- 24V charge alternator
- Alternator: single bearing alternator IP23, insulation class H/H
- Absorber
- Dry type air filter, double fuel filter, oil filter, coolant filter
- Main line circuit breaker
- Permanent Magnet Generator (PMG)
- Standard control panel
- Two 12V batteries, rack and cable
- Ripple flex exhaust pipe, exhaust siphon, flange, muffler
- User manual



Generator Ratings						
Prime Ratings (KW/KVA)	Standby Ratings (KW/KVA)	Standby Amps	P.F (COS $\phi$ )	Phase	HZ	Voltage
284/356	320/400	510	0.8	3	50	440/254
284/356	320/400	535	0.8	3	50	415/240
284/356	320/400	560	0.8	3	50	400/230
284/356	320/400	585	0.8	3	50	380/220

**Prime Power (PRP):** Prime power is available for an unlimited number of annual hours in variable load application, in accordance with GB/T2820-97 (eqv ISO8528) ; A 10% overload capability is available for a period of 1 hour within a 12-hour period of operation.

**Standby Power Rating (ESP):** The standby power rating is applicable for supplying emergency power for the duration of a utility power interruption. No overload, utility parallel or negotiated outage operation capability is available at this rating.

#### Sales Promises

Bargh afshan alborz provides a full line of brand new and high quality products. Each and every unit is strictly factory tested.

Warranty is according to our standard conditions: a, 15 months, counted on the day Bargh afshan alborz sold to the first buyer; b, One year after installation; c, 1000 running hours (accumulated); subject to the earlier one. Service and parts are available from Bargh afshan alborz or distributors in your location.

## Technical Data

BA.A-C400	Diesel Generating Set
<b>ENGINE DATA</b>	
Manufacturer / Model:	Cummins NTA 855 G4, 4-cycle
Air Intake System:	Turbo Charged and Search Refrigerated
Fuel System:	Electronic
Cylinder Arrangement:	6 In line
Displacement:	14 L
Bore and Stroke:	140*152 (mm)
Compression Ratio:	14.0:1
Rated RPM:	1500rpm
Max. Standby Power at Rated RPM:	320KW/434HP
Governor Type:	RSV Mechanical(Std) / Electronic (Optional)
<b>Exhaust System</b>	
Exhaust Gas Flow:	67.6 m <sup>3</sup> /min
Max Back Pressure:	10kPa
<b>Air Intake System</b>	
Air Flow:	24.5 m <sup>3</sup> /min
<b>Fuel System</b>	
100% ( Prime Power) Load:	76 L/h
75% (Prime Power) Load:	57 L/h
50% (Prime Power) Load::	39 L/h
<b>Oil System</b>	
Total Oil Capacity:	420 L
Oil Consumption:	≤4g/kwh
Engine Oil Tank Capacity:	38 L
<b>Cooling System</b>	
Total Coolant Capacity:	70 L
Thermostat:	82-95°C
Max Water Temperature:	104°C

## Technical Data

### BA.A-C400 Diesel Generating Set

#### ALTERNATOR SPECIFICATION

##### GENERAL DATA

Compliance with GB755, BS5000, VDE0530, NEMAMG1-22, IED34-1, CSA22.2 and AS1359 standards.

##### Alternator Data

Number of Phase:	3
Connecting Type:	3 Phase and 4 Wires, "Y" type connecting
Number of Bearing:	1
Power Factor:	0.8
Protection Grade:	IP23
Altitude:	≤1000m
Exciter Type:	Brushless, self-exciting
Insulation Class, Temperature Rise:	H/H
Telephone Influence Factor (TIF):	<50
THF:	<2%
Voltage Regulation, Steady State:	±1%
Alternator Capacity:	400 KVA
Alternator Efficiencies:	93

Air Cooling Flow:

##### GENERATING SET DATA

Voltage Regulation:	±5%
Voltage Regulation, Stead State:	±1%
Sudden Voltage Warp (100% Sudden Reduce):	+25%
Sudden Voltage Warp (Sudden Increase):	-20%
Voltage Stable Time (100% Sudden Reduce):	≤6S
Voltage Stable Time (Sudden Increase)	≤6S
Frequency Regulation, Stead State:	≤5%
Frequency Waving:	≤0.5%
Sudden Frequency Warp (100% Sudden Reduce):	+12%
Sudden Frequency Warp (Sudden Increase):	-10%
Frequency Recovery Time (100% Sudden Reduce):	≤5S
Frequency Recovery Time (Sudden Increase):	≤5S

## Technical Data

BA.A-C400 Diesel Generating Set		
Options		
Engine	Fuel System	Control System
Heater 2KW & 4KW Battery Charger 3.5A & 7A	Daily Fuel Tank Base Fuel Tank Water Separator Fuel Level Sensor	Auto Control Panel Remote Control Panel Auto Transfer Switch (ATS) Paralleling System
Anti Condensation Heater Drop CT (For Paralleling)	Rainproof Type Soundproof Type Container Type	Engine Parts Drawing List Spare Parts
Dimension & Weight		
Standard Configuration (Open Type)	With Base Fuel Tank	Soundproof Type
Overall Size: 3230 (mm) *1100 (mm) *2000 (mm) Weight: 3300 kg		Overall Size: 4400 (mm) *1430 (mm) *2270 (mm) Weight:4170 kg

## Technical Data

**BA.A-C400**

**Diesel Generating Set**

Standard Control Panel

Auto Module Control Panel

**Auto Module Control Panel** is the configuration for nobody on duty controlling generators. This kind of panel adopts auto module control system, with large LCD display to show the menu.



Features: MRS10-can receive remote output signal from ATS and realize auto start and stop of generators.

MRS16-can realize all functions of MRS10, add RS232 interface which can communicate with PC to realize remote operation.

AMF25-Auto Mains Failure controller, can realize all functions of MRS16, furthermore can detect ATS and control directly.

### Auto Parallel Control Panel

**Automatic Parallel Control Panel** This new automatic parallel system adopts intelligent modules, inserted and folded installed, no need the peripheral relay and logic circuit .



The main switch adopts electronic breaker or frame breaker, combined together with the generator, which is very reliable. One generator, one panel. The panel can be used both for singly and parallel. It is only need to parallel generator with such panel when the capability needs to be enlarged in the future.